



## 56K\* Faxmodem USB

Supports V.92† and V.90

### V.92

#### **Key Benefits**

##### **USB convenience and ease of use**

The Universal Serial Bus (USB) provides a simple Plug and Play installation. The 56K\* Faxmodem USB modem is hot-swappable (installs/uninstalls automatically) and is bus-powered so it doesn't require an external power supply.

##### **Internet Call Notification (ICN) puts you in charge of incoming calls**

ICN monitors online activity and lets you take full advantage of Modem on Hold – choose to accept or reject incoming calls while online.

##### **ControlCenter for optimum modem performance**

ControlCenter supports Modem on Hold and allows you to configure V.PCM speeds. Instant Update can download software updates automatically to your PC.



#### **Fastest 56K with USB Convenience**

U.S. Robotics is proud to introduce the V.92 international standard. V.92 offers more flexibility and greater control over your Internet experience than ever before. The U.S. Robotics 56K Faxmodem USB modem with V.92 technology offers not only fast downloads but great new features as well.

**Modem on Hold** makes the most of Call Waiting, Caller ID, and voice mail services from your phone company. If you take an incoming call using ICN, the modem “suspends” your online session during your conversation and lets you resume it afterwards without redialing. If you ignore the call, it will be routed automatically to your voice mail.

**Quick Connect** reduces the time it takes to make a connection to your service provider. By “remembering” the line conditions from the previous connection, the modem can bypass portions of its training sequence and get you online faster.

**V.PCM Upstream** allows the modem's upstream communication to reach speeds of up to 48 Kbps. With *ControlCenter* software, you choose whether to maintain the fastest possible downstream speed or a “balanced” connection of downstream and upstream communication.

The USB connector makes setting up and using the U.S. Robotics 56K Faxmodem USB modem a snap. And because it is USB powered, no external power supply is required for operation.

Even first-time modem users will find the U.S. Robotics 56K Faxmodem USB modem simple to install. All of the necessary fax software and V.92-enabling utilities are included on the Installation CD-ROM.



# 56K\* Faxmodem USB

Supports V.92<sup>†</sup> and V.90

## Features and Benefits

### V.92 Performance with USB Convenience

The U.S. Robotics 56K Faxmodem USB modem infuses U.S. Robotics quality and reliability with USB convenience and the enhanced performance of V.92:

- USB design: Simple Plug and Play installation and setup with no additional dedicated power source required.
- Fax and communications software included: Great capabilities and features include delayed and broadcast faxing, customisable interface, and Caller ID support (requires service from your local phone company).
- Complies with international standards: Connect with other modems, computers, and fax machines all over the world.
- Software upgradable: Online upgradability and downloadable software ensure that this modem will continue to meet your changing needs.

## Standards and Specifications

- Data: V.92, V.90, V.34, V.32bis, V.32, V.22bis, V.22, V.23, and V.21
- Data Error Control/Compression: V.42/V42bis and MNP2-4/5
- Fax: EIA 578 (Class 1) with V.17, V.29, V.27ter
- DTE interface: USB Version 1.1
- USB powered, consumption: 100 mA
- 4 LEDs: Rx, Tx, CD, Power
- Phone line interface: One RJ-11 socket
- Caller ID support (requires service from your local phone company; Caller ID may not be supported in some countries)

### Minimum System Requirements

- Windows 98SE/Me: Intel Pentium II 300 MHz or higher compatible PC, 128 MB RAM, 20 MB hard drive space
- Windows 2000/XP: Intel Pentium III 500 MHz or higher compatible PC, 128 MB RAM, 20 MB hard drive space
- USB port
- 2x or better CD-ROM drive
- Analogue phone line

### V.92 Requirements for this Modem

- V.92 features require V.92 56K ITU standard capable service provider
- V.92 Call Notification feature requires Call Waiting service from your local phone company
- V.92 Call Identification feature requires Call Waiting/Caller ID services from your local phone company

## Regulatory/Agency Approvals

- Complies with the 1999/5/EC directive

## Package Contents

- U.S. Robotics 56K Faxmodem USB external modem
- USB cable
- Phone cord
- Quick Installation Guide
- Installation Essentials CD-ROM, including user's guide, data/fax software, ControlCenter software, and Internet Call Notification

## Warranty

- 2-year limited warranty from date of purchase

## Model Number

5633



For connection to the Public Switched Telephone Network (PSTN)

*U.S. Robotics helped you get on the Internet, and we're keeping you connected with cutting edge technology. We're proud of our role in the history of the Internet, but even prouder of our role in the future – broadband, wireless, networking, and beyond. Our entire team, from customer support to engineering, is dedicated to keeping people connected worldwide – with information, entertainment, and each other. [www.usr.com](http://www.usr.com).*

\* Capable of receiving at up to 56K and sending at up to 48 Kbps (or 31.2 Kbps with V.90 server). Actual speeds may vary. Requires compatible phone line and server equipment.

† Actual speeds may vary. U.S. Robotics modems featuring V.92 enhancements are backward compatible and will negotiate the highest possible speed when connecting to an Internet Service Provider (ISP).